



®

BS Fuse Switch Selection

Fuse Switches to IEC 947-3, Fuses to IEC 269-1 (BS88-2)

MOTOR CONTROL AC23A RATINGS 415 VOLT 3 PHASE				FUSE SWITCH UFS NUMBER	ELECTRICAL DISTRIBUTION AC22A RATINGS 415 VOLT 3 PHASE		
le amps	kW	Maximum Fuse Size			le amps	Maximum Fuse Size	
32	15	32M63	A1	UFS 32 A1	32	32	A1
32	15	32M63	A2	UFS 32	50	50	A2
63	30	63M100	A2 A3	UFS 63	100	100	A2 A3
100	55	100M160	A2 A3	UFS 100 A3	100	100	A2 A3
160	75	200M250	*A4	UFS 160	160	160	*A4
				UFS 160 AC22	200	200	*A4
200	110	200M315	B1 B2	UFS 200	250	250	B1 B2
315	160	315M400	B1 B2 B3	UFS 315	355	355	B1 B2 B3
400	230	400M500	B1 B2 B3 B4	UFS 400	400	400	B1 B2 B3 B4
630	355	630M670	C1 C2 C3	UFS 630	630	630	C1 C2 C3
800	450	800	C1 C2 C3	UFS 800 C3	800	800	C1 C2 C3
800	450	800	C1 C2 C3	UFS 800	800	800	C1 C2 C3

* TO FIT A2 & A3 FUSES USE ADAPTOR KIT 62226-1